

## Product Specifications



### Sony CDXGT290 CD/MP3 Tuner with Front Aux in

#### Features:

- **MP3/WMA PLAYBACK** Playback your favourite MP3 CD compilations
- **S-MOSFET OUTPUT POWER: 52W x 4** produce cleaner, more accurate sounds with less distortion and a higher signal-to-noise ratio
- **FRONT AUX-IN** for direct connection of your portable music player
- **24-BIT DAC** Hear the difference with a cleaner, higher quality sound thanks to 24-bit DAC
- **EQ3 3 Band equalizer** with preset modes
- **FM x18 / AM x12 Preset Stations**
- **DETACHABLE FACEPLATE** for enhanced security when you leave your vehicle

#### Specifications:

##### General

- Pre Out Output Level (V) 2
- Pre Out Impedance (ohms) 220
- Maximum Output Power (4Ω, 1kHz) (W) 52
- Dimensions (W x H x D) 178 x 50 x 179mm
- Mounting Dimensions (W x H x D) 182 x 53 x 162mm
- Weight (kg) Approx. 1.2 kg
- Accessories RM-X151 Wireless Card Remote (Incl.)

##### Display Panel

- LCD Display
- Panel Type Slot-In
- Panel Finish Colour Gun Metallic
- Key Illumination Red

Design and specifications subject to change without notice.  
**Note: All products come with full Manufacturers Warranty.**



## Product Specifications

### Tuner

- Preset; FM18 / MW6 / SW12
- FM: Tuning Range (MHz) 87.5-107.9, 87.5-108.0
- MW: Tuning Range (kHz) 531-1602, 530-1710
- FM: Usable Sensitivity (75Ω) (dBf) 10
- FM: Intermediate Frequency (MHz) 150KHz
- FM: Selectivity (400kHz) (dB) 75
- FM: S/N Ratio (Mono) (dB) 70
- FM: Channel Separation (dB) 40
- FM: Frequency Response (Hz) 20-15k

### CD Deck

- CD-Text Display / Scroll
- Multi Session MP3 / WMA
- Frequency Response (Hz, dB) 10-20k, +/-1dB
- S/N Ratio (dB) 120

### Amplifier

- S-MOSFET Output Power 52W x 4
- Pre Out Rear / Sub Switchable
- Front Aux-In
- EQ3 Stage 2 (3-Band Equalizer / 7 Modes)
- Bass Treble Low / Mid / High

Design and specifications subject to change without notice.  
**Note: All products come with full Manufacturers Warranty.**