

CQ-DX100



DVD Reciever with DVD/CD Changer Control

- DVD Video and MP3 Playback
- High power amp (50W x4max)
- Divx Playback
- Front AV
- Dolby Digital Decoder

Features	Specifications
High-power amp (50W x 4 max.)	DVD/CD Chnager Control
Dolby Digital decoder (2-channel downmix)	18 FM and 6 AM presets with preset scan
DVD video and MP3 (CD-R/RW/DVD-R/RW) playback	Front AV input
DVD-R/RW playback	NTSC/PAL auto switch
DivX® playback	Removable front panel
SQ3 (3-band sound quality)	

Disc Player	
DVD Video Playback	2 ch
Video CD Playback	Yes
Music CD Playback	Yes
WMA/MP3 Playback	CD-R/RW,DVD-R/RW
Divx Playback	Yes
Amplifier	
Max. power output	50W x 4
Speaker impedance	4-8 ohms
Audio	
Frequency response (±1dB)	20Hz – 20kHz
Signal to noise ratio (IHF, A)	95dB
FM Radio	
Frequency Range	87.5-108.0 MHz
Usable sensitivity(S/N 30dB)	6dB / μV
Stereo Seperation(at 1 kHz)	35dB
AM Radio	
Frequency Range	531-1602kHz
Usable sensitivity(S/N 20dB)	27dB / μV
Input/Output	
Front AV Input (Video)	1.0Vp-p, 75 ohms
Front AV Input (Audio)	2.0V rms
Video output (Composite)	1.0Vp-p, 75 ohms
Audio output/preamp output	2V rms, 200 ohms
Dimensions	
Main unit (W x H x D)	17.8 x 5 x 16 cm